

Massachusetts Device Codes and Rated Lighting System Wattage Table

BX	Biax /Twin Tube Lamp	ELIG	EElectronic Ballast	HO	High Output Lamp
HW	Hard Wire Fixture	LPF	Low Power Ballast Factor < 0.80	STD	Standard Ballast or Lamp
EEMAG	Energy-Efficient Magnetic	HPF	High Power Ballast Factor > 1.0	VHO	Very High Output Lamp
EE	Energy-Efficient Lamp				

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Incandescent Lamps		
110015	15W INC	15
110020	20W INC	20
110025	25W INC	25
110034	34W INC	34
110036	36W INC	36
110040	40W INC	40
110042	42W INC	42
110045	45W INC	45
110050	50W INC	50
110052	52W INC	52
110054	54W INC	54
110055	55W INC	55
110060	60W INC	60
110065	65W INC	65
110067	67W INC	67
110069	69W INC	69
110072	72W INC	72
110075	75W INC	75
110080	80W INC	80
110085	85W INC	85
110090	90W INC	90
110093	93W INC	93
110100	100W INC	100
110120	120W INC	120
110125	125W INC	125
110135	135W INC	135
110150	150W INC	150
110200	200W INC	200
110300	300W INC	300
110448	448W INC	448
110500	500W INC	500
110750	750W INC	750
111000	1000W INC	1000
111500	1500W INC	1500

Low Voltage Halogen Fixture (includes Transformer)		
1R0020	20W LV HALOGEN FIXT	30
1R0025	25W LV HALOGEN FIXT	35
1R0035	35W LV HALOGEN FIXT	45
1R0042	42W LV HALOGEN FIXT	52
1R0050	50W LV HALOGEN FIXT	60
1R0065	65W LV HALOGEN FIXT	75
1R0075	75W LV HALOGEN FIXT	85

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Halogen/Quartz Lamps		
1T0035	35W HALOGEN LAMP	35
1T0040	40W HALOGEN LAMP	40
1T0042	42W HALOGEN LAMP	42
1T0045	45W HALOGEN LAMP	45
1T0050	50W HALOGEN LAMP	50
1T0052	52W HALOGEN LAMP	52
1T0055	55W HALOGEN LAMP	55
1T0060	60W HALOGEN LAMP	60
1T0072	72W HALOGEN LAMP	72
1T0075	75W HALOGEN LAMP	75
1T0090	90W HALOGEN LAMP	90
1T0100	100W HALOGEN LAMP	100
1T0150	150W HALOGEN LAMP	150
1T0200	200W HALOGEN LAMP	200
1T0250	250W HALOGEN LAMP	250
1T0300	300W HALOGEN LAMP	300
1T0350	350W HALOGEN LAMP	350
1T0400	400W HALOGEN LAMP	400
1T0425	425W HALOGEN LAMP	425
1T0500	500W HALOGEN LAMP	500
1T0750	750W HALOGEN LAMP	750
1T0900	900W HALOGEN LAMP	900
1T1000	1000W HALOGEN LAMP	1000
1T1200	1200W HALOGEN LAMP	1200
1T1500	1500W HALOGEN LAMP	1500

Mercury Vapor (MV)		
1V0040S	40W MERCURY	50
1V0050S	50W MERCURY	75
1V0075S	75W MERCURY	95
1V0100S	100W MERCURY	120
1V0175S	175W MERCURY	205
1V0250S	250W MERCURY	290
1V0400S	400W MERCURY	455
1V0700S	700W MERCURY	775
1V1000S	1000W MERCURY	1075
2V0400S	2/400W MERCURY	880

Low Pressure Sodium (LPS)		
1L0035S	35W LPS	60
1L0055S	55W LPS	85
1L0090S	90W LPS	130
1L0135S	135W LPS	180
1L0180S	180W LPS	230

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
High Pressure Sodium (HPS)		
1H0035S	35W HPS	45
1H0050S	50W HPS	65
1H0070S	70W HPS	90
1H0100S	100W HPS	130
1H0150S	150W HPS	190
1H0200S	200W HPS	240
1H0225S	225W HPS	275
1H0250S	250W HPS	295
1H0310S	310W HPS	350
1H0360S	360W HPS	435
1H0400S	400W HPS	460
1H0600S	600W HPS	675
1H0750S	750W HPS	835
1H1000S	1000W HPS	1085

Metal Halide (MH)		
1M0032S	32W METAL HALIDE	40
1M0050S	50W METAL HALIDE	65
1M0070S	70W METAL HALIDE	95
1M0100S	100W METAL HALIDE	120
1M0150S	150W METAL HALIDE	190
1M0175S	175W METAL HALIDE	205
1M0250S	250W METAL HALIDE	295
1M0360S	360W METAL HALIDE	430
1M0400S	400W METAL HALIDE	455
1M0750S	750W METAL HALIDE	825
1M1000S	1000W METAL HALIDE	1075
1M1500S	1500W METAL HALIDE	1615
1M1800S	1800W METAL HALIDE	1875

Pulse Start Metal Halide Lamp/Ballast		
1M0100P	100W MH CWA	128
1M0100R	100W MH LINEAR	118
1M0150P	150W MH CWA	190
1M0150R	150W MH LINEAR	172
1M0175P	175W MH CWA	208
1M0175R	175W MH Linear	190
1M0200P	200W MH CWA	232
1M0200R	200W MH LINEAR	218
1M0250P	250W MH CWA	288
1M0250R	250W MH LINEAR	265
1M0300P	300W MH CWA	342
1M0300R	300W MH LINEAR	324
1M0320P	320W MH CWA	365
1M0320R	320W MH LINEAR	345
1M0350P	350W MH CWA	400
1M0350R	350W MH LINEAR	375
1M0400P	400W MH CWA	455
1M0400R	400W MH LINEAR	430
1M0450P	450W MH CWA	508
1M0450R	450W MH LINEAR	480
1M0750P	750W MH CWA	815
1M0750R	750W MH LINEAR	805
1M1000P	1000W MH CWA	1080

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Two Foot T8 / T12 Systems		
1F20SSS	F20T12/HPF(1)	32
1F80BXE	1L2' F80BXE/ELIG	90
1F55BXE	1L2' F55BX/ELIG	56
2F17SSE	2L2' 17W T8/ELIG	37
2F17SSL	2L2' 17W T8/ELIG LOW POWER	27
2F17SSM	2L2' 17W T8/EEMAG	45
2F20SSS	F20T12/HPF(2)	56
2F24HSS	2L2' 24 T12HO/STD/STD	85
2F40BXE	2L2' F40BX/ELIG	72
2F50BXE	2L2' F50BX/ELIG	108
2F55BXE	2L2' 55BXE/ELIG	112
3F17SSE	3L2' 17W T8/ELIG	53
3F17SSL	3L2' 17W T8/ELIG LOW POWER	39
3F20SSS	F20T12/HPF(3)	78
3F40BXE	3L2' F40BX/ELIG	102
3F50BXE	3L2' F50BX/ELIG	162
3F55BXE	3L2' F55BX/ELIG	168
4F17SSE	4L2' 17W T8/ELIG	62
4F36BXE	4L2' F36BX/ELIG	148
4F40BXE	4L2' F40BX/ELIG	144
4F40BXH	4L 40W T5 (STD) HIGH LUMEN	170
4F50BXE	4L2' F50BX/ELIG	216
4F55BXE	4L2' F55BX/ELIG	224
5F40BXE	5L2' F40BX/ELIG	190
5F50BXE	5L2' F50BX/ELIG	270
5F55BXE	5L2' F55BX/ELIG	280
6F36BXE	6L2' F36BX/ELIG	212
6F40BXE	6L2' F40BX/ELIG	204
6F50BXE	6L2' F50BX/ELIG	324
6F55BXE	6L2' F55BX/ELIG	336
8F36BXE	8L2' F36BX/ELIG	296
8F40BXE	8L2' F40BX/ELIG	288
8F50BXE	8L2' F50BX/ELIG	432
8F55BXE	8L2' F55BX/ELIG	448
9F36BXE	9L2' F36BX/ELIG	318
9F40BXE	9L2' F40BX/ELIG	306
9F50BXE	9L2' F50BX/ELIG	486
9F55BXE	9L2' F55BX/ELIG	504

Three Foot T8 / T12 Systems		
1F30SEM	1L3' 30W T12 EE/EEMAG	38
1F30SES	1L3' 30W T12 EE/STD	42
1F30SSS	1L3' 30W T12 STD/STD	46
1F25SSE	1L3' 25W T8/ELIG	24
2F30SEE	2L3' 30W T12 EE/ELIG	49
2F30SEM	2L3' 30W T12 EE/EEMAG	66
2F30SES	2L3' 30W T12 EE/STD	73
2F30SSS	2L3' 30W T12 STD/STD	80
2F25SSE	2L3' 25W T8/ELIG	47
2F25SSM	2L3' 25W T8/EEMAG	65
3F30SSS	3L3' 30W T12 STD/STD	140
3F30SES	3L3' 30W T12 EE/STD	127
3F25SSE	3L3' 25W T8/ELIG	68
4F25SSE	4L3' 25W T8/ELIG	88

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Four Foot F48 T12 Systems		
1F48SES	1L4' F48T12EE/STD	50
1F48SSS	1L4' F48T12/STD	60
2F48SES	2L4' F48T12EE/STD	82
2F48SSS	2L4' F48T12/STD	102
3F48SES	3L4' F48T12EE/STD	132
3F48SSS	3L4' F48T12/STD	162
4F48SES	4L4' F48T12EE/STD	164
4F48SSS	4L4' F48T12/STD	204

Four Foot F48HO T12 Systems		
1F48HES	1L4' F48HO/EE/STD	80
1F48HSS	1L4' F48HO/STD/STD	85
2F48HES	2L4' F48HO/EE/STD	135
2F48HSS	2L4' F48HO/STD/STD	145
3F48HES	3L4' F48HO/EE/STD	215
3F48HSS	3L4' F48HO/STD/STD	230
4F48HES	4L4' F48HO/EE/STD	270
4F48HSS	4L4' F48HO/STD/STD	290

Four Foot F48VHO T12 Systems		
1F48VES	1L4' F48VHO/EE/STD	123
1F48VSS	1L4' F48VHO/STD/STD	138
2F48VES	2L4' F48VHO/EE/STD	210
2F48VSS	2L4' F48VHO/STD/STD	240
3F48VES	3L4' F48VHO/EE/STD	333
3F48VSS	3L4' F48VHO/STD/STD	378
4F48VES	4L4' F48VHO/EE/STD	420
4F48VSS	4L4' F48VHO/STD/STD	480

Four Foot T12 Systems		
1F40SEE	1L4' EE/ELIG	38
1F40SEM	1L4' EE/EEMAG	40
1F40SES	1L4' EE/STD	50
1F40SSE	1L4' STD/ELIG	46
1F40SSM	1L4' STD/EEMAG	50
1F40SSS	1L4' STD/STD	57
2F40SEE	2L4' EE/ELIG	60
2F40SEM	2L4' EE/EEMAG	70
2F40SES	2L4' EE/STD	80
2F40SSE	2L4' STD/ELIG	72
2F40SSM	2L4' STD/EEMAG	86
2F40SSS	2L4' STD/STD	94
3F40SEE	3L4' EE/ELIG	90
3F40SEM	3L4' EE/EEMAG	110
3F40SES	3L4' EE/STD	130
3F40SSE	3L4' STD/ELIG	110
3F40SSM	3L4' STD/EEMAG	136
3F40SSS	3L4' STD/STD	151
4F40SEE	4L4' EE/ELIG	120
4F40SEM	4L4' EE/EEMAG	140
4F40SES	4L4' EE/STD	160
4F40SSE	4L4' STD/ELIG	144
4F40SSM	4L4' STD/EEMAG	172
4F40SSS	4L4' STD/STD	188
6F40SSS	6L4' STD/STD	282

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Four Foot T8 Systems		
1F32SSE	1L4' T8/ELIG	30
1F32SSL	1L4 T8/ELIG LOW POWER	26
1F32SSM	1L4' T8/EEMAG	37
2F32SSE	2L4' T8/ELIG	60
2F32SSH	2L4' T8/ELIG HIGH LMN	78
2F32SSL	2L4 T8/ELIG LOW PWR	52
2F32SSM	2L4' T8/EEMAG	70
3F32SSE	3L4' T8/ELIG	88
3F32SSH	3L4' T8/ELIG HIGH LMN	112
3F32SSL	3L4 T8/ELIG LOW POWER	76
3F32SSM	3L4' T8/EEMAG	107
4F32SSE	4L4' T8/ELIG	112
4F32SSH	4L4' T8/ELIG HIGH LMN	156
4F32SSL	4L4 T8/ELIG LOW PWR	98
4F32SSM	4L4' T8/EEMAG	140
5F32SSE	5L4' T8/ELIG	148
5F32SSH	5L4' T8/ELIG HIGH LMN	190
6F32SSE	6L4' T8/ELIG	174
8F32SSH	8L4' T8/ELIG HIGH LMN	312

Five Foot T8 / T12 Systems		
1F40HSE	1L5' HO/STD/ELIG	59
1F60HSM	1L5' HO/STD/EEMAG	90
2F40HSE	2L5' HO/STD/ELIG	123
2F40TSE	2L5' T8/ELIG	68
2F60HSM	2L5' HO/STD/EEMAG	178
3F40TSE	3L5' T8/ELIG	106

Six Foot T12 & T12HO Systems		
1F72HSS	1L6' F72HO/STD/STD	113
1F72SSM	1L6' STD/EEMAG	80
1F72SSS	1L6' STD/STD	95
2F72HSE	2L6' T8 HO/ELIG	160
2F72HSM	2L6' F72HO/STD/EEMAG	193
2F72HSS	2L6' F72HO/STD	195
2F72SSM	2L6' STD/EEMAG	135
2F72SSS	2L6' STD/STD	173

Eight Foot T12HO Systems		
1F96HES	1L8' HO/EE/STD	125
1F96HSS	1L8' HO/STD/STD	135
2F96HEE	2L8' HO/EE/ELIG	170
2F96HEM	2L8' HO/EE/EEMAG	207
2F96HES	2L8' HO/EE/STD	227
2F96HSE	2L8' HO/STD/ELIG	195
2F96HSM	2L8' HO/STD/EEMAG	237
2F96HSS	2L8' HO/STD/STD	257
3F96HES	3L8' HO/EE/STD	352
3F96HSS	3L8' HO/STD/STD	392
4F96HEE	4L8' HO/EE/ELIG	340
4F96HEM	4L8' HO/EE/EEMAG	414
4F96HES	4L8' HO/EE/STD	454
4F96HSE	4L8' HO/STD/ELIG	390
4F96HSM	4L8' HO/STD/EEMAG	474
4F96HSS	4L8' HO/STD/STD	514

EXISTING LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Eight Foot T12VHO Systems		
1F96VES	1L8'VHO/EE/STD	200
1F96VSS	1L8'VHO/STD/STD	230
2F96VES	2L8'VHO/EE/STD	390
2F96VSS	2L8'VHO/STD/STD	450
3F96VES	3L8'VHO/EE/STD	590
3F96VSS	3L8'VHO/STD/STD	680
4F96VES	4L8'VHO/EE/STD	780
4F96VSS	4L8'VHO/STD/STD	900

Eight Foot T8 Systems		
1F59SSE	1L8'T8/ELIG	60
1F80SSE	1L8'T8 HO/ELIG	85
2F59SSE	2L8'T8/ELIG	109
2F59SSL	2L8'T8/ELIG LOW PWR	100
2F80SSE	2L8'T8 HO/ELIG	160
1F96SEE	1L8'EE/ELIG	60
1F96SES	1L8'EE/STD	83

Eight Foot T8 Systems		
1F96SSE	1L8' STD/ELIG	70
1F96SSS	1L8' STD/STD	100
2F96SEE	2L8' EE/ELIG	109
2F96SEM	2L8' EE/EEMAG	123
2F96SES	2L8' EE/STD	138
2F96SSE	2L8' STD/ELIG	134
2F96SSM	2L8' STD/EEMAG	158
2F96SSS	2L8' STD/STD	173
3F96SES	3L8' EE/STD	221
3F96SSS	3L8' STD/STD	273
4F96SEE	4L8' EE/ELIG	218
4F96SEM	4L8' EE/EEMAG	246
4F96SES	4L8' EE/STD	276
4F96SSE	4L8' STD/ELIG	268
4F96SSM	4L8' STD/EEMAG	316
4F96SSS	4L8' STD/STD	346

PROPOSED LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
LED Exit Signs		
1E0002	2.0 WATT LED	2
1E0003	3.0 WATT LED	3
1E0005	5.0 WLED	5
1E0005C	0.5 WATT LEC	0.5
1E0008	8.0 WLED	8
1E0015	1.5 WATT LED	1.5
1E0105	10.5 WATT LED	10.5

Compact Fluorescents (CFL's)		
2C0007S	2/7W COMPACT HW	18
1C0005S	5W COMPACT HW	7
1C0007S	7W COMPACT HW	9
1C0009S	9W COMPACT HW	11
1C0011S	11W COMPACT HW	13
1C0013S	13W COMPACT HW	15
1C0018E	18W COMPACT HW ELIG	20
1C0018S	18W COMPACT HW	20
1C0022S	22W COMPACT HW	24
1C0023E	1/23W COMPACT HW ELIG	25
1C0026E	26W COMPACT HW ELIG	28
1C0026S	26W COMPACT HW	28
1C0028S	28W COMPACT HW	30
1C0032S	32W CIRCLINE HW	34
1C0042E	1/42W COMPACT HW ELIG	48
1C0044S	44W CIRCLINE HW	46
1C0057E	1/57W COMPACT HW ELIG	65
1C2232S	22/32W CIRCLINE HW	58
1C2D10E	10W 2D COMPACT HW ELIG	12
1C2D16E	16W 2D COMPACT HW ELIG	18
1C2D21E	21W 2D COMPACT HW ELIG	22
1C2D28E	28W 2D COMPACT HW ELIG	28
1C2D38E	38W 2D COMP.HW ELIG	36
1C3240S	32/40W CIRCLINE HW	80
2C0005S	2/5W COMPACT HW	14
2C0009S	2/9W COMPACT HW	22
2C0011S	2/11W COMPACT HW	26
2C0013E	2/13W COMPACT HW ELIG	28
2C0013S	2/13W COMPACT HW	30
2C0018E	2/18W COMP. HW ELIG	40
2C0026E	2/26W COMP. HW ELIG	54
2C0032E	2/32W COMPACT HW ELIG	68
2C0042E	2/42W COMPACT HW ELIG	100
3C0009S	3/9W COMPACT HW	33
3C0013S	3/13W COMPACT HW	45
3C0018E	3/18W COMPACT HW ELIG	60
3C0026E	3/26W COMPACT HW ELIG	82
3C0032E	3/32W COMPACT HW ELIG	114
3C0042E	3/42W COMPACT HW ELIG	141
4C0018E	4/18W COMPACT HW ELIG	80
4C0026E	4/26W COMPACT HW ELIG	108
4C0032E	4/32W COMPACT HW ELIG	152
6C0026E	6/26W COMPACT HW ELIG	162
6C0032E	6/32W COMPACT HW ELIG	228

PROPOSED LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Compact Fluorescents (CFL's) (cont)		
6C0042E	6/42W COMPACT HW ELIG	282
8C0026E	8/26W COMPACT HW ELIG	216
8C0032E	8/32W COMPACT HW ELIG	304
8C0042E	8/42W COMPACT HW ELIG	376

T5 Systems		
1F21SSE	1L3' 21W T5/ELIG	24
1F28SSE	1L4' 28W T5/ELIG	32
1F39HSE	1L3' 39W T5HO/ELIG	42
1F54HSE	1L4' 54W T5HO/ELIG	59
1F14SSE	1L2' 14W T5/ELIG	16
2F14SSE	2L2' 14W T5/ELIG	34
1F24HSE	1L2' 24W T5HO/ELIG	29
2F24HSE	2L2' 24W T5HO/ELIG	52
3F24HSE	3L4' T5HO/ELIG	80
2F21SSE	2L3' 21W T5/ELIG	47
2F28SSE	2L4' 28W T5/ELIG	63
2F39HSE	2L3' 39W T5HO/ELIG	85
2F54HSE	2L4' 54W T5HO/ELIG	117
3F54HSE	3L4' 54W T5HO/ELIG	177
4F54HSE	4L4' 54W T5HO/ELIG	234
5F54HSE	5L4' 54W T5HO/ELIG	294
6F54HSE	6L4' 54W T5HO/ELIG	351
8F54HSE	8L4' 54W T5HO/ELIG	468
10F54HSE	10L4' 54W T5HO/ELIG	585

Two Foot High Efficient T8 Systems		
1F17ESL	1L2' 17W T8EE/ELEE LOW PWR	14
1F17ESN	1L2' 17W T8EE/ELEE	17
1F17ESH	1L2' 17W T8EE/ELEE HIGH PWR	20
2F17ESL	2L2' 17W T8EE/ELEE LOW PWR	27
2F17ESN	2L2' 17W T8EE/ELEE	32
2F17ESH	2L2' 17W T8EE/ELEE HIGH PWR	40
3F17ESL	3L2' 17W T8EE/ELEE LOW PWR	39
3F17ESN	3L2' 17W T8EE/ELEE	46
3F17ESH	3L2' 17W T8EE/ELEE HIGH PWR	61

Three Foot T8 Systems		
1F25ESL	1L3' 25W T8EE/ELEE LOW PWR	21
1F25ESN	1L3' 25W T8EE/ELEE	24
1F25ESH	1L3' 25W T8EE/ELEE HIGH PWR	30
2F25ESL	2L3' 25W T8EE/ELEE LOW PWR	40
2F25ESN	2L3' 25W T8EE/ELEE	45
2F25ESH	2L3' 25W T8EE/ELEE HIGH PWR	60
3F25ESL	3L3' 25W T8EE/ELEE LOW PWR	58
3F25ESN	3L3' 25W T8EE/ELEE	67
3F25ESH	3L3' 25W T8EE/ELEE HIGH PWR	90

Four Foot T8 High Efficient / Reduce Wattage Systems		
1F25EEH	1L4' 25W T8EE/ELEE HIGH PWR	30
1F25EEE	1L4' 25W T8EE/ELEE	22
1F25EEL	1L4' 25W T8EE/ELEE LOW PWR	19
2F25EEH	2L4' 25W T8EE/ELEE HIGH PWR	57
2F25EEE	2L4' 25W T8EE/ELEE	43
2F25EEL	2L4' 25W T8EE/ELEE LOW PWR	37
3F25EEH	3L4' 25W T8EE/ELEE HIGH PWR	86

PROPOSED LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
Four Foot T8 High Efficient / Reduce Wattage Systems (cont)		
3F25EEE	3L4' 25W T8EE/ELEE	64
3F25EEL	3L4' 25W T8EE/ELEE LOW PWR	57
4F25EEH	4L4' 25W T8EE/ELEE HIGH PWR	111
4F25EEE	4L4' 25W T8EE/ELEE	86
4F25EEL	4L4' 25W T8EE/ELEE LOW PWR	75
1F28EEH	1L4' 28W T8EE/ELEE HIGH PWR	33
1F28EEE	1L4' 28W T8EE/ELEE	24
1F28EEL	1L4' 28W T8EE/ELEE LOW PWR	22
2F28EEH	2L4' 28WT8EE/ELEE HIGH PWR	64
2F28EEE	2L4' 28W T8EE/ELEE	48
2F28EEL	2L4' 28W T8EE/ELEE LOW PWR	42
3F28EEH	3L4' 28W T8EE/ELEE HIGH PWR	96
3F28EEE	3L4' 28W T8EE/ELEE	72
3F28EEL	3L4' 28W T8EE/ELEE LOW PWR	63
4F28EEH	4L4' 28W T8EE/ELEE HIGH PWR	126
4F28EEE	4L4' 28W T8EE/ELEE	94
4F28EEL	4L4' 28W T8EE/ELEE LOW PWR	83
1F30EEH	1L4' 30W T8EE/ELEE HIGH PWR	36
1F30EEE	1L4' 30W T8EE/ELEE	26
1F30EEL	1L4' 30W T8EE/ELEE LOW PWR	24
2F30EEH	2L4' 30WT8EE/ELEE HIGH PWR	69
2F30EEE	2L4' 30W T8EE/ELEE	52
2F30EEL	2L4' 30W T8EE/ELEE LOW PWR	45
3F30EEH	3L4' 30W T8EE/ELEE HIGH PWR	103
3F30EEE	3L4' 30W T8EE/ELEE	77
3F30EEL	3L4' 30W T8EE/ELEE LOW PWR	68
4F30EEH	4L4' 30W T8EE/ELEE HIGH PWR	133
4F30EEE	4L4' 30W T8EE/ELEE	101
4F30EEL	4L4' 30W T8EE/ELEE LOW PWR	89
1F32EEH	1L4' 32W T8EE/ELEE HIGH PWR	38
1F32EEE	1L4' 32W T8EE/ELEE	28
1F32EEL	1L4' 32W T8EE/ELEE LOW PWR	25
2F32EEH	2L4' 32W T8EE/ELEE HIGH PWR	73
2F32EEE	2L4' 32W T8EE/ELEE	53
2F32EEL	2L4' 32W T8EE/ELEE LOW PWR	47
3F32EEH	3L4' 32W T8EE/ELEE HIGH PWR	109
3F32EEE	3L4' 32W T8EE/ELEE	82
3F32EEL	3L4' 32W T8EE/ELEE LOW PWR	72
4F32EEH	4L4' 32W T8EE/ELEE HIGH PWR	141
4F32EEE	4L4' 32W T8EE/ELEE	107
4F32EEL	4L4' 32W T8EE/ELEE LOW PWR	95
6F32EEH	6L4' 32W T8EE/ELEE HIGH PWR	218
6F32EEE	6L4' 32W T8EE/ELEE	168
6F32EEL	6L4' 32W T8EE/ELEE LOW PWR	146

LED Lighting Fixtures		
1L010	10 WATT LED	10
1L011	11 WATT LED	11
1L012	12 WATT LED	12
1L014	14 WATT LED	14
1L015	15 WATT LED	15
1L016	16 WATT LED	16
1L017	17 WATT LED	17
1L023	23 WATT LED	23
1L025	25 WATT LED	25
1L028	28 WATT LED	28

PROPOSED LIGHTING SYSTEMS		
Device Code	Device Description	Rated Watts
LED Lighting Fixtures (cont)		
1L029	29 WATT LED	29
1L035	35 WATT LED	35
1L043	43 WATT LED	43

LED Integral Replacement Lamps		
1L004	4 WATT LED MR16	04
1L005	5 WATT LED MR16	05
1L006	6 WATT LED MR16	06
1L007	7 WATT LED MR16	07
1L008	8 WATT LED MR16	08
1L009	9 WATT LED MR16	09

LED Cooler & Freezer Case Fixtures		
1L009	9 WATT LED	09
1L010	10 WATT LED	10
1L011	11 WATT LED	11
1L012	12 WATT LED	12
1L013	13 WATT LED	13
1L014	14 WATT LED	14
1L017	17 WATT LED	17
1L018	18 WATT LED	18
1L022	22 WATT LED	22
1L024	24 WATT LED	24
1L026	26 WATT LED	26
1L029	29 WATT LED	29
1L034	34 WATT LED	34

LED Low Bay - Garage & Canopy Fixtures		
1L030	30 WATT LED STD DRIVER	39
1L040	40 WATT LED STD DRIVER	49
1L050	50 WATT LED STD DRIVER	60
1L060	60 WATT LED STD DRIVER	71
1L080	90 WATT LED STD DRIVER	116
1L120	120 WATT LED STD DRIVER	139
1L140	140 WATT LED STD DRIVER	164
1L160	160 WATT LED STD DRIVER	186
1L180	180 WATT LED STD DRIVER	211
1L200	200 WATT LED STD DRIVER	233
1L220	220 WATT LED STD DRIVER	256
1L240	240 WATT LED STD DRIVER	279